

# Model: TRALUN318LIPW2K-C

The Community Controls TRALUN318LIPW2KC, is a key chain style transmitters operating at 318 MHz. They have been designed for use with programmable telephone entry, security, and access control systems operating with a 318 MHz frequency receiver. The protocol is Linear® compatible.

#### Compatible with 318Mhz:

Linear® Monarch®, Stingray®, RCS® and Chameleon® Transmitters

## **FEATURES**

- ChargeGuard® Battery Status LED Indicator
- Available with a coil as a combo remote that accepts HID®, Mango®, AWID® and Securakey® protocols
- Durably designed with robust materials to withstand harsh conditions and repeated use
- 318 Mhz
- Two Buttons (Blue)
- Key Chain Model
- Linear Compatible
- 5 Year Warranty
- Programmable
- Operates with all Wiegand 26 bit control system
- Available with custom facility codes and Serial numbers











### **SPECIFICATIONS**

Battery: 1 x 12V - 23A

Battery Life: 18 - 24 months Number Combinations: 16,384 Different Facility Codes: 64

Operating Temperature: -20°F to 131°F (-20°C to 55°C)

Overall Dimensions: 2.51" x 1.52" x 0.58"

Weight: 1 oz. (20 gr.)

### Also available in 1 and 4 button.









#### **KEEP YOUR CUSTOMERS COMING BACK!**

We can brand your transmitter with your logo and information.



PH 800-284-2837 **FX** 801-972-1202

www.communitycontrols.com